



ANODE OUTPUTS

- R1, R4: 110 kΩ (±5 %, 1/10 W)
- R2, R3: 330 kΩ (±5 %, 1/10 W)
- R5-R15: 180 kΩ (±5 %, 1/10 W)
- R16: 1 MΩ (±5 %, 1/10 W)
- R17-R19: 51 Ω (±5 %, 1/10 W)
- R20: 10 kΩ (±5 %, 1/10 W)
- C1-C4: 0.01 μF (200 V)

MAX HIGH VOLTAGE: -1000 V
 DIVIDER CURRENT: 350 μA (-HV = -1000 V)
 DIVIDER RATIO 0.6:1.8:2.4:1:1:1:1:1:1:1:1:1:1:1:1

M16F SOCKET ASSY (FOR R8520MOD-03-M16F)	ITEM	NOTE	DATE	NAME		VOLTAGE DIVIDER CIRCUIT	
				DRAWING NUMBER		5A-6631	DATE
APPROVED BY: <i>[Signature]</i>							Feb. 18 2002
CHECKED BY: 229						HAMAMATSU PHOTONICS K.K.	
DRAWN BY: S. KATO	SCALE						